

Europower generating sets with **asynchronous Soga** or **synchronous Soga/GTS** alternator, protection **IP54**, 3000rpm, 50Hz, 4 stroke**IP54**

Article code	TYPE	Price in EURO (ex. VAT)	kVA max.	kVA cont.	Amp.		Engine HONDA	HP max.	kW max.	cm ³	Tank (l)	Cons. @75% load (l/h)	Autonomy @75% load (h)	Version	Dimensions (cm)	kg	dB(A) @ 7m	LWA
		Alternator			1 ~ 230V	3 ~ 400V												
400012012	EP3000-IP54	on request (Soga)	3	2.7	11.7	-	GX200	5.2	3.8	196	3.1	1.3	2.4	A-F-O-R-TM	65x42x48	52	70	95
400012013	EP3500-IP54	on request (Soga)	3.5	3.2	13.9	-	GX270	7.9	5.8	270	5.3	2	2.7	A-F-O-R-TM	67x51x56	64	71	96
SA380	EP6000-IP54	on request (So)	6	5.5	24	-	GX390	11.1	8.2	389	6.1	2.4	2.5	A-AVR-F-O-R-TM	77x51x56	93	72	97
SA448	EP8000T-IP54	on request (So)	8	7.5	11.7	10.8	GX390	11.1	8.2	389	6.1	2.4	2.5	B-AVR-F-O-R-TM	77x51x56	96	72	97
SA479	EP12000TE-IP54	on request (So)	12.5	11	17	16	GX630	19	14	688	20	4.2	4.8	B-AVR-E-F-FPm-h-O-TM	102x55x60	148	75	*

Europower **60Hz** generating sets, **3600rpm****60Hz**

Article code	TYPE	Price in EURO (ex. VAT)	kVA max. (60Hz)	kVA cont.	Amp.	Volt	Engine HONDA	HP max.	kW max.	cm ³	Tank (l)	Cons. @75% load (l/h)	Autonomy @75% load (h)	Version	Dimensions (cm)	kg	dB(A) @ 7m	LWA
		Alternator																
SA177	EP2700-60	on request (S)	2.7	2.4	10.4	230	GX160	4.9	3.6	163	3.1	1.2	2.6	A-F-O-R-Th	58x42x44	37	73	*
SA077	EP3700-60	on request (S)	3.7	3.4	14.8	230	GX200	5.8	4.3	196	3.1	1.6	1.9	A-F-O-R-Th	58x42x44	42	73	*
SA267	EP4800-60	on request (S)	4.8	4.3	19	230	GX270	8.6	6.3	270	5.3	2.4	2.2	A-F-O-R-Th	77x51x56	65	74	*
SA178	EP7200-60	on request (S)	7.2	6.5	28	230	GX390	11.8	8.7	389	6.1	2.9	2.1	A-F-O-R-Th	83x51x56	72	78	*

Generators with * cannot be used outdoors in the EU. For applications of generating sets indoors, or if you want to integrate these generators in vehicles, please contact us.